

Coaxial Band-stop Filter

Stopband: 5.15-5.85GHz

Model: TLRF-5150M-5850M-S

TLRF-5150M-5850M-S is a coaxial band-stop filter with a stop band frequency from 5.15 to 5.85 GHz and a pass band frequency from DC to 4.45GHz and 6.4 to 11GHz. The maximum insertion loss of the filter is 1.5 dB and the minimum rejection is 40 dB.

Features:

- Stopband Frequency Range 5.15 to 5.85GHz
- Low Insertion Loss
- Lower Cost
- High Rejection

Applications:

- Communication Systems
- Radar Systems
- Sub-assemblies

Electrical Characteristics:


Parameter	Min	Typ	Max	Units
Stopband Frequency range	5.15		5.85	GHz
Passband Frequency range	DC-4.45 & 6.4-11			GHz
Stopband Rejection	40			dB
Passband Insertion Loss			1.5	dB
Passband VSWR			2	:1
Power Handling			5	W
Impedance		50		Ohms

Environmental And Physical Characteristics:

Description	Parameter	Units
Operating Temperature	-20 to +60	°C
Input /Output Connector	SMA Female/SMA Female	
Size	141*35*18	mm

Outline Drawing:

Unit:mm




ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:

Base Number	Description	Revision
TLRF-5150M-5850M-S	Coaxial Band-stop Filter, Stopband: 5.15-5.85GHz, Passband: DC-4.45GHz&6.4-11GHz, Stopband rejection: 40dB Min	Rev.1.0

Typical Performance Data:



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.