

Coaxial Band-stop Filter

Stopband: 5.15-5.35GHz

Model: TLRF-5G15-5G35-S

TLRF-5G15-5G35-S is a coaxial band-stop filter with a stop band frequency from 5.15 to 5.35 GHz and a pass band frequency from DC to 4.95GHz and 5.55 to 11GHz. The maximum insertion loss of the filter is 2 dB and the minimum rejection is 40 dB.

Features:

- Stopband Frequency Range 2.4 to 2.5GHz
- Low Insertion Loss
- Lower Cost
- High Rejection

Applications:

- Communicatin Systems
- Radar Systems
- Sub-assemblies


电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	单位 Units
阻带频率范围 Stopband Frequency rang	5.15		5.35	GHz
通带频率范围 Passband Frequency range	DC-4.95 & 5.55-11			GHz
阻带抑制 Stopband Rejection	40			dB
通带插损 Passband Insertion Loss			2	dB
通带驻波 Passband VSWR			1.7	:1
耐功率 Power Handling		10		W
阻抗 Impedance		50		Ohms

环境和机械特性 Envriental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
操作温度 Operating Temperature	0 to +40	°C
输入/输出接口 Input /Output Connector	SMA Female/SMA Female	
尺寸 Size	150*27.8*20	mm

Unit:mm




ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TLRF-5G15-5G35-S	Coaxial Band-stop Filter,Stopband: 5.15-5.35GHz,Passband: DC-4.95GHz&5.55-11GHz, Stopband rejection: 40dB Min	Rev.1.0

典型曲线 Typical Performance Data:



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.