

Coaxial Band-pass Filter

31-33.4/ 2.92 Female

Model: TLBF-31G-33G4-E

TLBF-31G-33G4-E is a coaxial band-pass filter with a passband frequency from 31 to 33.4 and a rejection frequencies @26 and 38.4GHz. The nominal insertion loss of the filter is 1.5 dB and the typical rejection is 50 dB.

Features:

- Passband Frequency Range 31 to 33.4 GHz
- Low Insertion Loss
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations

Electrical Characteristics:


Parameter	Min	Typ	Max	Units
Passband Frequency range	31		33.4	GHz
Passband Insertion Loss			1.5	dB
Pass Band Ripple			1.2	dB
Rejection	≥50dB@fc±5GHz			dB
Power Handling			20	W
Input VSWR			1.6	:1
Output VSWR			1.6	:1
Impedance	50			Ohms

Envrionmental And Physical Characteristics:

Description	Parameter	Units
Operating Temerature	-40 To +70	°C
Storage Temperature	-40 to +70	°C
Connectors	2.92 Female	

Outline Drawing:

Unit:mm;




ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:

Base Number	Description	Revision
TLBF-31G-33G4-E	Coaxial Band-pass Filter, Passband frequency range: 31 to 33.4 GHz, Passband Insertion Loss: 1.5dB, 2.92 Female	Rev.1.0

典型曲线 Typical Performance Data:



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.