

Coaxial Band-stop Filter

Stopband: 1710-1790MHz

Model: TLRF-1710M-1790M-E

TLRF-1710M-1790M-E is a coaxial band-stop filter with a stop band frequency from 1710 to 1790MHz and a pass band frequency from DC to 1675MHz and 1825 to 5000MHz. The nominal insertion loss of the filter is 1.5 dB and the minimum rejection is 60 dB.

Features:

- Stopband Frequency Range 1710 to 1790MHz
- Lower Cost
- Low Insertion Loss
- High Rejection

Applications:

- Communicatin Systems
- Radar Systems
- Sub-assemblies

电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	单位 Units
阻带频率范围 Stopband Frequency rang	1710		1790	MHz
通带频率范围 Passband Frequency range	DC-1675 & 1825-5000			MHz
阻带抑制 Stopband Rejection	60			dB
通带插损 Passband Insertion Loss		1.5	2	dB
通带驻波 Passband VSWR			1.5	:1
耐功率 Power Handling			20	W
阻抗 Impedance		50		Ohms

环境和机械特性 Envirionmental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
工作温度 Operating Temperature	-30 to +70	°C
输入/输出接口 Input /Output Connector	SMA Female/SMA Female	
尺寸 Size	245*47*22	mm

外形图 Outline Drawing: Unit:mm



ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TLRF-1710M-1790M-E	Coaxial Band-stop Filter, Stopband: 1710-1790MHz, Passband: DC-1675MHz&1825-5000MHz, Stopband rejection: 60dB Min	Rev.1.0