

Coaxial Band-stop Filter

Stopband: 2780-2980MHz

Model: TLRf-2780-2980-N

TLRF-2780-2980-N is a coaxial band-stop filter with a stop band frequency from 2780 to 2980 MHz and a pass band frequency from DC to 2630MHz and 3130 to 7100MHz. The maximum insertion loss of the filter is 2 dB and the minimum rejection is 50 dB.

Features:

- Stopband Frequency Range 2780 to 2980MHz
- Low Insertion Loss
- Lower Cost
- High Rejection

Applications:

- Communicatin Systems
- Radar Systems
- Sub-assemblies


电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	单位 Units
阻带频率范围 Stopband Frequency rang	2780		2980	MHz
通带频率范围 Passband Frequency range	DC-2630 & 3130-7100			MHz
阻带抑制 Stopband Rejection	50			dB
通带插损 Passband Insertion Loss			2	dB
通带驻波 Passband VSWR			1.7	:1
耐功率 Power Handling			20	W
阻抗 Impedance		50		Ohms

环境和机械特性 Envrionmental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
操作温度 Operating Temperature	-10 to +50	°C
输入/输出接口 Input /Output Connector	N Female/N Female	
尺寸 Size	200*34*20	mm

外形图 Outline Drawing: Unit:mm



ESD Protection: Strictly
adhere to ESD precautions
to prevent electrostatic
damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TLRF-2780-2980-N	Coaxial Band-stop Filter, Stopband: 2780-2980MHz, Passband: DC-2630MHz&3130-7100MHz, Stopband rejection: 50dB Min	Rev.1.0