

Waveguide to Coax Adapter, End Launch WR-15/1.85mm Female/50-67GHz

Model: TL-15WCA1.85E

The TL-15WCA1.85E is end launch waveguide to coax adapters that cover the frequency range of 50 to 67 GHz. It is designed for an efficient transition between the rectangular waveguide and 1.85 mm coax connector.

Features:

- Operating Frequency 50 to 67GHz
- Lower Insertion Loss and VSWR
- Instrumentation Grade
- DC Short Circuit

Applications:

- Test Lab
- Instrumentations
- Sub-assemblies



Electrical Characteristics:


Parameter	Min	Typ	Max	Units
Frequency Range	50		67	GHz
Insertion Loss		0.5	0.9	dB
VSWR		1.3		:1
Power Handling			10	W

Envrionmental And Physical Characteristics:

Parameter	Description	Units
Operating Temerature	-40 To +85	°C
Storage Temerature	-40 to +85	°C
Material	Aluminum	
Finish	Gold Plated	
Coax Connector	1.85mm Female	
Waveguide	WR-15/UG-385/U-M	

Outline Drawing:

Unit:mm; Tolerance:±0.1mm




ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:


Base Number	Description	Revision
TL-15WCA1.85E	Waveguide to Coax Adapter, End Launch WR15/1.85mm Female,50-67GHz	Rev.1.0

Typical Performance Data:

VSWR vs Frequency



Insertion Loss vs Frequency



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.