Suzhou Talent Microwave,Inc
sales@talentmw.com
www.talentmw.com

Waveguide to Coax Adapter, Right Angle

WR-10/1.0mm Male/75-110GHz Model: TL-10WCA1.0MR-CU

The TL-10WCA1.0MR-CU is right angle waveguide to coax adapters that cover the frequency range of 75 to 110GHz. It is designed for an efficient transition between the rectangular waveguide and 1.0 mm coax connector.

Features:

- Operating Frequency 75 to 110GHz
- Lower Insertion Loss and VSWR
- Instrumentation Grade
- DC Short Circuit

Applications:

- Test Lab
- Instrumentations
- Sub-assemblies

Electrical Characteristics:

Parameter	Min	Typ	Max	Units
Frequency Range	75		110	GHz
Insertion Loss		6	1.0	dB
VSWR		1..3		:1
Power Handing			10	W


Envrionmental And Physical Characteristics:


Parameter	Description	Units
Operating Temerature	-40 To +85	℃
Storage Temerature	-40 to +85	℃
Material	Brass	
Finish	Gold Plated	
Coax Connector	1.0mm Male	
Waveguide	WR-10/UG-387/U-M	

Suzhou Talent Microwave,Inc
sales@talentmw.com
www.talentmw.com

Outline Drawing:

Unit:mm; Tolerance:±0.1mm





ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:

Base Number	Description	Revision
TL-10WCA1.0MR-CU	Waveguide to Coax Adapter, Right Angle WR-10/1.0mm Male,75-110GHz	Rev.1.0